

This Page Is Inserted by IFW Operations
and is not a part of the Official Record

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images may include (but are not limited to):

- BLACK BORDERS
- TEXT CUT OFF AT TOP, BOTTOM OR SIDES
- FADED TEXT
- ILLEGIBLE TEXT
- SKEWED/SLANTED IMAGES
- COLORED PHOTOS
- BLACK OR VERY BLACK AND WHITE DARK PHOTOS
- GRAY SCALE DOCUMENTS

IMAGES ARE BEST AVAILABLE COPY.

**As rescanning documents *will not* correct images,
please do not report the images to the
Image Problems Mailbox.**




PCT

WORLD INTELLECTUAL PROPERTY ORGANIZATION
International Bureau

INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(51) International Patent Classification ⁶ : G06K 11/18	A1	(11) International Publication Number: WO 97/36257 (43) International Publication Date: 2 October 1997 (02.10.97)
(21) International Application Number: PCT/US97/04003 (22) International Filing Date: 14 March 1997 (14.03.97) (30) Priority Data: 08/624,022 27 March 1996 (27.03.96) US (71) Applicant: GATEWAY 2000, INC. [US/US]; 610 Gateway Drive, P.O. Box 2000, North Sioux City, SD 57049-2000 (US). (72) Inventors: AUTRY, Sidney, David; Apartment 109, 250 Courtyard Drive, Dakota Dunes, SD 57049 (US). SCHINDLER, Jeffrey; 4301 Far Hills Road, Sioux City, IA 51104 (US). (74) Agent: VIKSNINS, Ann, S.; Schwegman, Lundberg, Woessner & Kluth, P.O. Box 2938, Minneapolis, MN 55402 (US).	(81) Designated States: AU, CA, JP, European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE). Published <i>With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i>	

(54) Title: HAND-HELD REMOTE CONTROLLER WITH TRIGGER SELECTION BUTTON



(57) Abstract

An entertainment system has a personal computer as the heart of the system with a large screen VGA quality monitor and a radio frequency remote control device. The remote control device has a pointing device and a plurality of keys on top of the device and a trigger-like button mounted on the bottom of the device which functions as a mouse selection button.

FOR THE PURPOSES OF INFORMATION ONLY

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakistan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

HAND-HELD REMOTE CONTROLLER WITH TRIGGER SELECTION BUTTONField of the Invention

The present invention relates to remote control units for electronic devices and in particular to remotely controlling a home entertainment system.

5 Background of the Invention

The consumer electronics industry has created many stand alone products for specific functions, such as television viewing, video recording and playback, broadband video receivers, playing recorded music and broadcast music. Some devices combine functions, such as the combination TV/VCR, and the audio
10 cassette/AM/FM receiver to name a couple. One direction that consumers are moving is toward larger televisions located within a family room or living room with accompanying high quality stereo. Multiple components are required, each providing separate functions. A large screen television based on a 19 inch to 40 inch picture tube, or 46 inch to 60 inch projection system is used and viewed
15 from a distance of two to five meters. The television includes a tuner for receiving and decoding National Television Systems Committee (NTSC) signals, infrared receiver circuitry for a remote control, and in many cases stereo and surround sound integrated into it, making it a very expensive device. Further, the consumer likely has a video recorder/player, and perhaps a cable box/set top
20 box to receive cable or satellite transmission which may also include a video tuner and other electronics to handle modulated, compressed and encrypted video signals. In addition, a consumer is also likely to have a separate stereo system complete with CD player, tuner and other audio attachments, such as speakers. This duplicates much of the functionality of the television system and
25 adds to the cost of a home entertainment center.

Most consumer electronic devices come with remote control devices, which as in the case of the television above, require sensing circuitry to receive and process the signals from the remotes. Such controls are typically based on IR signals which can be interrupted by someone walking in front of it, and are
30 not able to be used in a different room from the receiver. While special remote control devices which can be programmed to control multiple consumer

electronic devices found in a home entertainment center exist, there is little consistency between the controls on such remotes and the remote becomes bulky and difficult to use as more buttons are added to control the additional functions. Furthermore, there is no good way to use different remote control units to control different programs generating the information displayed in various windows on the screen. While some remotes operate in conjunction with on-screen programming functions, the buttons found on such remotes cannot easily operate the more advanced graphical user interfaces available on personal computers. This leads to confusion of the consumer, and the classic case of the blinking "12:00" as consumers become frustrated trying to master all the protocols required to appropriately control their electronic devices. Trying to program a VCR to record a program in the future can also be quite difficult. The expense of the additional circuitry in all the devices to accomplish these functions is borne by the consumer.

Multimedia based personal computers today are configured with CD Rom drives, and speakers as well as graphics drivers for displaying graphics on a monitor attached to the computer. CD Rom drives are capable of both reading data, such as computer programs, and reading audio information such as music which is output from the attached speakers. Multimedia titles for running on a PC usually are distributed on CD Rom, and involve such things as animated encyclopedias and other books, as well as games that may incorporate video clips which can be shown on a PC display. More and more of the video information on such CDS is compressed in accordance with Motion Picture Experts Group (MPEG) standards and requires commercially available software or circuitry to decompress it and process it for display. The display signal is typically of VGA quality. Some add on products for PCS even provide a connection to video feeds from multiple sources for playing in a window on the monitor screen. Typically, the computer has a video graphics adapter (VGA or SVGA) card which processes all the information to be displayed on a monitor and the monitor itself is basically a picture tube that shows only what it is sent with very little processing. However, most PC displays are small, and not

suitable for viewing by multiple people at the same time. It often happens that when a family gets a new program such as a game, animated book or educational game, everyone wants to see it being used for the first time, and they huddle around a small display and vie for positions. In addition, there is no good way
5 for multiple users to interact on a single computer. For viewing video feeds from cable or satellite, large screen consumer television sets are most commonly used in the home entertainment center.

As can be seen, there is great duplication of function between the consumer electronics and personal computers, both of which are more and more
10 likely to be found in a family room or great room of a home. This duplication of function leads to much more money being spent to fully outfit the home entertainment center and provide additional functions. When one component fails, since it has duplicate function, it is expensive to replace. One system that tried to solve some of the above problems is shown in US Patent No. 5,192,999
15 to Graczyk et al. That system has a television circuit and an audio circuit within a personal computer, both of which are controlled by a remote control device. The television circuit is used to receive common cable or broadcast video signals in NTSC format, which inherently have a lower quality than video signals currently broadcast by digital broadcasting satellite. NTSC format signals are
20 interlaced, which means that every other line is refreshed during each scan of the picture tube. For example, odd lines would be refreshed during a first scan, and even lines during a second scan. Since there are 60 scans per second, odd lines are refreshed 30 times per second, and even lines are refreshed 30 times per second. VGA monitors refresh at least 60 times per second, providing a more
25 coherent spacial and temporal image. The NTSC signal is a lower bandwidth signal than digital MPEG, which has a much higher bandwidth and allows productive use of even higher resolution monitors. While Graczyk et al. does convert the NTSC signals to VGA format for display by a data quality analog monitor, the signal quality is limited because of the lower bandwidth
30 transmission. NTSC signals have a great effect on the type of text that can be displayed. With an interlaced display, the text displayed in normal fonts appears

to jump as alternate lines are refreshed. There have been several attempts to design fonts that minimize this jump effect, but none have worked well. A VGA display, refreshing each line with every scan of the tube, does not have this problem, and provides a much sharper and readable image for text.

5 The monitor described by Graczyk is shown as a standard PC analog VGA monitor, and reference is commonly made to a single user. Such monitors are fairly small, having a maximum viewing area of 17.5 inches (44.5 cm) at the high end of the PC market. They are not nearly suitable for viewing in a home entertainment environment. They are designed for close viewing, having pixels
10 very close together. Current home entertainment systems are much larger and expensive due to all the other circuitry they have as described above.

 One satellite broadcast system is that provided by DirecTV, a unit of GM Hughes Electronics. Direct Broadcast Satellites, "DBS" provide more than 150
15 channels of high-quality MPEG based video, sound and data to 18 inch (45.7 cm) receiving antennas. Rights to make subscriber terminals are licensed by DirecTV, and several other companies contributing technology. News Datacom Corporation provides encryption and security for the DBS system, providing decryption keys, software and an access card for each subscriber terminal. Thomson Consumer Electronics provides consumer subscriber terminals in the
20 form of set top boxes called integrated receiver/decoders "IRDs" which convert the high-quality television signals into NTSC for showing on a standard television. Each IRD demodulates, decodes, decrypts and outputs video and data, which is displayed on a subscriber television. Error correction, decompression and demultiplexing to separate out video data from other data is
25 also provided in the IRD. While S-Video output is provided, there is no provision for monitor/VGA quality output capability. Other sources of MPEG based video include optical fiber based cable systems, compact disk, video clips available on the Internet network, both old and proposed HDCCD (high-definition compact disk) formats, and other existing and proposed satellite, digital cable,
30 and asynchronous-transfer mode ("ATM")-based systems as well as wireless digital broadcasts.

Summary of the Invention

A hand held remote control device is used to control a cursor displayed on a monitor as part of a graphical user interface into a home entertainment system controlled by a multipurpose computer system. Support for remote control of both the personal computer and the monitor functions is provided in the personal computer as well as standard PC VGA graphic display functions normally associated with personal computers.

The hand held remote has a pointing device, such as a trackball, a miniature joystick, or a touchpad for controlling the cursor displayed on the monitor. Given the entertainment room environment, a touchpad provides the further benefit of being able to withstand greasy popcorn and chicken fingers which might foul other pointing devices.

A trigger-like selection button located on the bottom of the hand held remote acts as a mouse selection button and permits one-handed drag-and-drop operations using the index finger when holding and pointing the remote. In this position, the user's thumb is on top of the remote to manipulate the pointing device, the index finger is on the trigger, with the rest of the fingers and the heel of the hand provides a resting place for the bulk of the device. A trigger guard is provided that partially shrouds the trigger to prevent it from being inadvertently activated when setting the remote down.

Additionally, the hand held remote has a plurality of keys representing alphanumeric symbols and cursor control functions. The keys also act as associated keys for selecting functions identified by the cursor.

The hand held remote transmits signals to the computer that identify the keys pressed, the state of the trigger, and the movements of the pointing device. The signals control what channel is being displayed on the home entertainment television set, or cause a recorded program to fast forward, play or reverse on the home entertainment video cassette recorder. The remote is also used to move to the next image or otherwise control a program designed to display pictures taken on a digital camera. One signal instructs the computer to execute a key-mapping program which permits the user to interactively change the functional

interpretation of the signals by the computer. For example, the same key used to select the channel can be remapped to swap between active applications executing in the computer.

5 The signals transmitted are preferably RF signals typically in the megahertz range, but can also be IR or other suitable form of radiation. RF signals have the advantage over infrared "IR" signals in that they are not interrupted by someone walking between the remote and the receiver. Light source interference and jamming of other IR receivers is minimized by using RF signals. An RF remote may also be used in a different room from the receiver.

10 This invention allows the user to execute standard computer software that normally requires a mouse or other button-equipped device from a remote location and using only one hand while at the same time serving as a remote control device for a home entertainment system controlled by the personal computer.

15

Brief Description of the Drawings

Figure 1 is a block diagram of a home entertainment system for processing and displaying high quality video in accordance with the present invention.

20 Figure 2 is a top view representation of the end of a shell connector for coupling to a monitor in accordance with the present invention.

Figure 3 is a block diagram showing major components of a personal computer in the home entertainment system of Figure 1.

25 Figure 4 is a block diagram of a tuning circuit in the personal computer of Figure 3.

Figure 5 is a block diagram of a video graphics adapter in the personal computer of Figure 3.

Figure 6 is a block diagram of an audio card in the personal computer of Figure 3.

30 Figure 7 is a block diagram showing input and output connectors which are provided in the personal computer of Figure 3.

Figure 8 is a block functional diagram showing the functional elements of a database storing programming information which can be displayed on the system of Figure 1.

Figure 9a is a top view of a hand held remote control device in one embodiment of the present invention.

Figure 9b is a cut away side view of a hand held remote control device in one embodiment of the present invention.

Figure 9c is a cut away side view of an alternative hand held remote control device in one embodiment of the present invention.

Figure 10 is a top view of a keyboard remote control device in one embodiment of the present invention.

Figure 11a is a high level flow diagram showing how commands from the remote controls of Figures 9a-c and 10 are processed.

Figure 11b is a high level block diagram showing the association of remote control devices to applications.

Figure 12 is a block diagram showing power adjustment controls for the remote control devices of Figures 9a-c and 10.

Figure 13 is a block diagram representation of a user interface displayed on the screen of the present invention.

Figure 14a-f are block diagram representations of a user interface for interacting with the home entertainment system of the present invention.

Figure 15 is a block diagram representation of a video-conferencing system based on the home entertainment system of the present invention.

Figure 16 is a block diagram representation of an alternative video conferencing system based on the home entertainment system of the present invention.

Description of the Preferred Embodiment

In the following detailed description of the preferred embodiment, reference is made to the accompanying drawings which form a part hereof, and in which is shown by way of illustration specific preferred embodiments in which the invention may be practiced. These embodiments are described in

sufficient detail to enable those skilled in the art to practice the invention, and it is to be understood that other embodiments may be utilized and that structural, logical and electrical changes may be made without departing from the spirit and scope of the present inventions. The following detailed description is, therefore, not to be taken in a limiting sense, and the scope of the present inventions is defined only by the appended claims.

Numbering in the Figures is usually done with the hundreds and thousands digits corresponding to the figure number, with the exception that the same components may appear in multiple figures. Signals and connections may be referred to by the same number or label, and the actual meaning should be clear from the context of use.

In Figure 1, a home entertainment system is shown generally at 110. External to the home entertainment system, a satellite 112, which in one preferred embodiment is a HS601 model, operated by Hughes at a 101 degree west longitude geosynchronous orbital location, transmits signals comprising 150 channels of modulated digital video, audio and data signals at a frequency of about 12 GHz. The satellite signals are received by the home entertainment system 110 by an antenna 114 containing a low noise block converter amplifier. The antenna is preferably about 18 inches in diameter and receives left and right hand circularly polarized signals between 12.2 and 12.7 GHz. The antenna provides a "downconverted-spectrum" signal between 950 and 1450 MHz via a coaxial cable or other suitable communication medium 116 to a system device 118, such as a personal computer or other system or circuitry capable of processing data. Suitable antennas are already being manufactured and sold by RCA Corporation by direct sales and through numerous major retail chains such as Radio Shack. The system 118 contains circuitry and software to further processes the signals from the antenna, generally demodulating and decoding the signal to produce a VGA signal. The VGA signal is provided via a standard VGA compatible monitor cable 120 to drive a large screen data quality monitor 122 suitable for viewing in a family room or entertainment type room environment. The system 118 provides for user input by means of remote

controls 124 and 126. Remote control 124 comprises a handheld size device with standard television controls and numeric keypad, and in one embodiment, VCR controls and a pointing device. It provides RF (radio-frequency) or IR (infrared) control signals received by the system 118. Remote control 126 is a
5 full function personal computer keyboard, with additional standard television and VCR controls, pointing device which is preferably in the form of a touchpad, and it also provides RF control signals to the system 118. RF control signals were selected over IR or hardwired in one embodiment due to the home entertainment environment. It allows the system to be in a different room from
10 the monitor 122, or if in the same room, a clear line of sight is not required. In another embodiment, IR control signals were selected because of the availability of many standard circuitry at low cost. Further detail of the remote control devices is provided below.

The monitor cable 120 is a standard type cable typically used on VGA
15 display devices, and comprises up to fifteen electrical conductors, interfacing with the monitor 122 in a D series shell connector indicated at 210 in Figure 2. The fifteen leads, some of which are blank, end in pins in the connector which is a molded over, shielded, triple row, 15 position, subminiature D, straight male plug. The leads are labeled and identified in a table indicated generally at 212
20 next to the representation of shell connector 210. The monitor contains a suitable female connector for receiving the male shell connector 210.

The monitor 122 in Figure 1 is preferably capable of displaying at least VGA quality data and video. At least 640 by 480 pixels of resolution are displayable on the monitor. Alternative monitors of higher quality, such as
25 SVGA providing an even greater number of pixels are also used in a further embodiment. Many common graphics cards support multiple such formats, providing great flexibility. The tube size is 33 inches with a diagonal viewing size of 31 inches. An alternative tube size of 29 inches with 27 inch viewing area is lower cost and more suitable for an entry model entertainment system.
30 Monitor 122 preferably contains an analog tube with an aspect ratio of 4 by 3, supports VGA input, has a dot pitch of approximately .8 to .95 millimeters for

the 33 inch tube and .65 to .8 millimeters for the 29 inch tube with a
misconvergence of 1 to 1.5 millimeters, a bandwidth of 15 MHz, a brightness of
about 33 FL. One CRT which may be used is manufactured by Mitsubishi,
having a model and type number of M79KKZ111X. The above specifications
5 may easily be modified for larger tube sizes, but are designed to provide optimal
viewability from a distance of less than two to about four meters for a
combination of data and high quality video. If the viewing distance is desired to
be less, the tube size and dot pitch should be decreased. If the tube size is not
decreased, more pixels would need to be displayed for adequate viewing of data.
10 SVGA monitors providing more lines would be more appropriate. Standard
digital monitor controls to control brightness, contrast, vertical and horizontal
sizing and positioning, on/off (rest/resume) are also provided, with both a user
accessible manual control panel, and circuitry for receiving control information
from personal computer 18 in via monitor cable 120. Further embodiments of
15 monitor 22 include larger displays of 35 and 40 inches viewable and LCD large
projection screen type displays. Both aspect ratios of 4:3 and 16:9, commonly
referred to as wide screen are supported.

Further detail of the functional blocks of system 118 are shown in Figure
3. A processor 310 resides on a system board containing an industry standard
20 PCI bus 312. A random access memory 314 is coupled to both the processor 310
for direct access, and to the PCI bus 312 for direct access by other components
also coupled to the PCI bus 312.

The other components comprise a receiver 316, video graphics adapter,
VGA converter card 318, sound card 320 and modem 322. An RF receiver 324
25 is coupled to standard keyboard and mouse ports, which in turn are coupled
through a standard keyboard/mouse adapter to an ISA bus 326 to processor 310.
Both keyboard 126 and handhold remote 124 transmit RF signals identifying the
key pressed, as well as a signal identifying the source of the key signal. The RF
signals are typically in the megahertz range, but can also be IR or other suitable
30 form of radiation. RF signals have the advantage over infrared "IR" signals in
that they are not interrupted by someone walking between the remote and the

receiver. This is especially important during a drag-and-drop type of activity. If the signal is interrupted for example, a needed document might be dropped on a trash can icon, causing the document to be unintentionally deleted. Light source interference and jamming of other IR receivers is minimized by using RF signals. It may also be used in a different room from the receiver.

RF receiver 324 receives the RF signals, which provide indications of the keys being pressed along with the identity of the remote control device sending the signal. RF receiver 324 comprises an ISA board or module plugged into both standard keyboard and mouse ports. The board contains RF receiver circuitry which receives the RF signals, decodes them and routes them to the appropriate port for processing. A system controller program running on processor 310 supervises software drivers which are programmed to distinguish between the sources, and control which program the remote key signals affect. If the handheld remote is activated, the key signals usually would control what channel is being displayed, or cause a recorded program to fast forward, play or reverse. It could however be selected to move to the next image in a program designed to display pictures taken on a digital camera. Keyboard keys are more likely to control a computer program application such as a word processor, spread sheet or electronic mail program. However, the television like controls might be used to override the remote hand held television controls in channel selection.

Further elements of the preferred embodiment of the present invention include a tape drive 330 for backup of data and storage of video information, such as a movie or other program, a fixed disk drive 332 for storing programs and data, a CD ROM drive 334, and a diskette drive 336, all as commonly known in the personal computer art. A pair of speakers 338 and 340 are also provided. A power supply and associated control circuitry is indicated at 342, and is coupled to the RF receiver 324 to receive signals representative of power on and power off commands from the remote control devices. Power circuitry 342 maintains power to the RF receiver 324 even when the rest of the system is shut down to ensure that the power on signal is received and executed. To avoid

accidental powering off of the system, two consecutive power off signals must be received before the system is powered down.

In one preferred embodiment, processor 310 is a 100 MHz Pentium processor, RAM 314 comprises a minimum of 16 megabytes, disk drive 332 is a 1.5 gigabyte IDE hard drive, the CD ROM drive 334 is a quad speed, 3 disc changer, and the fax/modem is a standard 28.8 k bits-per-second (or "KBAUD") modem. It should be noted that components in personal computers are getting faster, smaller and cheaper with higher capacity. It is easily anticipated that larger memories and faster modems and processors will be preferable over the next 20 plus years. In an alternative preferred embodiment, a very high speed processor 310 is used, and receiver 316 simply comprises circuitry to transform received signals into a digital format. The remainder of the functions of the receiver 316 and VGA card 318 are performed by software routines to receive, tune multiple simultaneous channels, decompress, perform error checking and correction and convert the digital signals into digital VGA format. The VGA card 318 in this embodiment simply comprises a digital to analog converter.

Receiver 316 is shown in further detail in Figure 4. A tuner 410 receives the direct broadcast signal from antenna 114 via standard coaxial cable 116. The broadcast signal is 150 channels of high-quality television, including data, compressed in accordance with motion picture expert group, MPEG-1 standards with MPEG-2 expected to be available in the near future. The information is carried on an approximately 12 gigahertz carrier, and the receiver 316 selects channels from the carrier and performs analog to digital conversion of the signal. A demodulator 412 is coupled to tuner 410 for demodulation of the digital signals. Forward error correction is provided via standard Viterbi and Reed-Solomon algorithms at block 414. The output of block 414 comprises an encrypted digital signal, in one embodiment encrypted in accordance with data encryption standards "DES." While it is not important to precisely reproduce the video signal, it is much more important to get the data such as computer programs and financial information accurately. The above error correction algorithms are designed to reduce the error rate for data to 10^{-12} errors per byte of

data. For video and audio, an error rate of 10^{-8} is acceptable. The error corrected encrypted digital signal is supplied to a decryption and demultiplexing block 416. Block 416 is coupled to a conditional access card 418 which provides the key for decrypting the digital signal. Upon separating the multiplexed digital
5 decrypted signal, it is provided as digital MPEG conforming signals via a connector 420 to PCI bus 312.

In operation, when processor 310 executes a command, such as changing a channel, it sends the command over the PCI bus 312 to receiver 316, where tuner 410 tunes in a different channel, and the video signals are processed and
10 sent on to VGA card 318 and sound card 320. Once on PCI bus 312, the digital MPEG signal may follow several different courses. In one embodiment, a buffer is allocated from RAM 314 to hold a user selected amount of compressed video data or information comprising computer programs. The same buffer concept may be applied to disk drive 332, which is useful for holding an even larger
15 amount of information. Tape drive 330 is preferably an 8 millimeter tape device, and is useful for storing entire programs of data or MPEG compressed video/audio information. The tradeoffs for each storage device are clear, with the cost of storage per megabyte increasing with the speed with which it may be retrieved. Hence, while RAM provides very fast access, it is a limited resource,
20 and does not make sense to use for much more than a few seconds of video related data. Also, it is a transitory memory in that it does not persist if power is removed. It is most useful for buffering about 10 seconds worth of video information. While it is not possible to predict how long a block of data will play when converting to video, 10 seconds is about 15 megabytes of data. The
25 tape drive 330 is the cheapest form of data storage, but is not randomly accessible. In other words, it can take some time for the tape to move to the right place before desired data can be retrieved for playing. However, it does provide the most cost effective storage for linear playback of movies and television shows. A disk drive 332 is has an average access time of about 10 milliseconds,
30 making it a nice tradeoff between tape and RAM for buffering portions of video

information and allowing the user to select and quickly play back desired buffered video. It, like tape is also persistent.

When the MPEG data is buffered, a FIFO type of buffer is used, with new information written over the oldest information when the buffer is full.

- 5 Through use of the television and VCR remote controls on handheld remote 124 and keyboard 126, VCR-like instant replay functions are provided from the buffered MPEG data. The buffered data is sent back under processor 310 control via the PCI bus 312 to the VGA card 318 for display on monitor 122.

- The VGA card 318 is now described with reference to Figure 5. In
10 Figure 5, a controller 510 is coupled to the PCI bus to receive MPEG encoded video, and other normal personal computer display information such as graphics and text. If controller 510 detects MPEG data on PCI bus 312, it routes it to a decoder 512 with associated dynamic random access memory of 2 megabytes, DRAM 514. Decoder 512 decodes the MPEG data in accordance with MPEG
15 standards. A commercially available chip from SGS-Thompson Microelectronics, part number STi3520 is one such decompressor chip which performs the decompression. DRAM 514 is used as a buffer to assist in the decoding, since large amounts of data are required at one time to decode MPEG data. Audio information from the decoded MPEG data is provided to a header
20 516 for transmission to the sound card 320. The decoded video signal in YUV color encoding is provided back to controller 510 which then places the video information into a dynamic random access memory or video random access memory, VRAM 518. A converter 520 retrieves the information from VRAM 518 and generates standard analog VGA display signals on a cable adapter 522
25 which mates with shell 210 in Figure 2 for display.

- Other audio video inputs are provided on VGA card 318, including a standard cable connector at 524 coupled to a video tuner circuit 526. Tuner 526 provides both an audio output on line 528 to header 516, and an audio video signal to a video decoder 530 via line 532. Line 532 is also coupled to a video
30 multiplexer 540, which selects one of at least two NTSC compatible audio video signals it receives to an audio video out panel connector 542. Video decoder 530

also receives audio video inputs from further panel connectors, comprising RCA jack 544, S-video pin 546 and a second RCA jack 548. The video signals provided on these lines are decoded by decoder 530 into YUV video output on line 550, which also receives decoded MPEG signals from decoder 512. Both
5 these signals are available for display by VGA display via controller 510 without conversion to NTSC. An alternative is to route the signals on line 550 to a YUV to NTSC converter 552, which feeds video multiplexer 540 for display on a standard television of NTSC signals. However, conversion to NTSC results in an inferior picture being generated from what is received in either S-video or
10 from the antenna 114 as represented by the MPEG signals on PCI bus 312. By not converting to NTSC, the entire transmitted image may be displayed. Prior art NTSC conversion lead to a cropping of the image to ensure that the image presented was not degraded at the edges. The present invention provides the ability to scale for provision of the entire transmitted image without quality loss
15 at the edges, since it provides a digital video signal. No overscan is required as is needed to ensure smooth display borders for NTSC analog transmissions.

Sound card 320 is shown in further detail in the functional block diagram of Figure 6. Both FM synthesis and wavetable synthesis are provided at 610 and 612 respectively. Their outputs are mixed or multiplexed at 614 and provided to
20 a mixer and coder/decoder 616 which provides a line out 618 containing SoundBlaster compatible output for connection to standard speakers if desired. In a further embodiment, surround sound compatible output is provided. Mixer 616 also has a microphone input line 620, a CD audio digital line in 622 one embodiment, and a CD audio analog line in 624. A multiplexer 626 also
25 multiplexes multiple input lines into mixer 616. A line in 628 and two audio/video lines 630 and 632 are multiplexed by multiplexer 626, as are signals received from header 516 via lines 634 and 636. Line 634 is coupled through header 516 to tuner 526, providing an audio signal from channels on cable connector 524. Header 516 is also coupled to MPEG decoder 512 to provide
30 MPEG PCM (pulse-code modulation) audio through digital to analog converter

640 to line 636. Lines 636 and 634 are also coupled through a further multiplexer 642 to provide a line out of VCR compatible audio on a line 644.

Figure 7 shows multiple ports available on the back panel of the personal computer 118, and on the cards shown in Figures 4, 5 and 6. The back panel connections are shown generally at 710. The audio video inputs comprise RCA jack 544 and audio left and right speaker connectors 630 for receiving audio video input from a VCR or game machine, S-video pin 546 and auxiliary RCA jack 548 for receiving audio video input from a VCR, camcorder or laserdisc and left and right audio connectors 712. Audio video out connectors 542 and 644 are available on the back panel 710 for coupling to a VCR for recording. Sound card 320 contains connectors 618, 620 and 628 on the mounting bracket, plus a game port 720. VGA card 318 contains the coaxial cable connection 524 and the VGA output port 522. Digital receiver card 316 contains the coaxial cable connector to coaxial cable 116, and a slot for the conditional access card 418 indicated at 720. Slot 720 may be a standard PCMCIA slot (also referred to as CardBus or PC Card), or any other type of connector desired, such as one specified by News Datacom, who is providing such digital satellite system (DSS) cards for settop boxes. By providing the above connectors and ports on the back side of the personal computer, they are accessible for easy wiring, but also out of view in the home entertainment center.

The DSS signal on coax cable 116 also contains data relating to television programming scheduling and closed caption information. In some video broadcast services, the closed caption information is contained in the vertical blanking interval of video signals. This information is captured by the receiver 316 and separated out from the video and audio signals, and provided on the PCI bus to RAM 324 where it is accessible to processor 310. It can also be stored on any other storage device capable of storing text or other digital data. As shown in Figure 8, the text is stored directly into a database 812 on RAM 324 or disk drive 332. In one preferred embodiment, database 812 comprises flat files of the entire text provided by receiver 316. No organization is applied to it other than sequential as received. A search engine 814 running on processor 310

accepts user queries indicated at 816 in the form of key words. All standard commercial database query functionality, such as proximity searching, query by example, wildcard letters, etc are applicable. Search engine 814 then applies the query to the database 812 and supplies the results back through the VGA card 318 for display. The data is preferably formatted as specified by the user, most likely in terms of the title of the program, the time that it will be on, and the channel that it will be on. Further information, such as descriptions of the program, and at least partial credits including director and actors may also be specified to be provided by the user. Closed caption information is stored separately from the programming information and may be queried separately. Where a separate data channel contains all the closed caption information for the channels containing video information, it is easy to store the closed caption information for all the channels. However, if it is required to decode each video MPEG channel, then only the closed caption information from one channel at a time is stored. An auto surf function cycles through desired channels, picking up portions of closed caption information, which can then also be searched. This is very useful when looking for current event type programming. Perhaps a user is interested in a particular place, or when a particular feature on a desirable topic starts. A query to review all the current and past mentions of the place or feature during live programming can quickly alert the user to broadcasts satisfying the query. Where closed caption is not supported, the sound track from video is fed into a speech recognition program 820 running on processor 310 which recognizes at least a few words from current television programming, and will improve with time and advancement in linguistic parsing. For now, only the words that are recognized are fed into yet another partition of the database which can be independently searched.

Various views of the hand held remote control 124 are shown in Figures 9a, 9b, and 9c. A 19 millimeter optical trackball 910 is integrated into the remote, and functions just as any other pointing device for personal computers, generating cursor control signals that are transmitted to the personal computer 118. In a further preferred embodiment, the cursor control device is a miniature

joystick shown at 911 disposed on a top portion of the remote control 124 in Figure 9C, that is operated by a finger, such as a thumb, being placed on top of the stick and pushing in the direction of desired cursor movement. In a further embodiment, the cursor control device can be a touchpad incorporated into the top portion of the remote control 124. A trigger-like selection button is provided at 913 on a bottom portion of the remote control device 124, which is convenient for use by an index finger if holding and pointing the remote in a natural position. It is also useful as a pseudo trigger for many games, and for one handed dragging and dropping of icons. The trigger 913 is protected from unintentional activation by trigger guard 950 which is formed into the plastic of the hand held remote control 124 during manufacture and partially shrouds the trigger 913. A selection button is provided at 912 for the user to press to select functions on the personal computer that the cursor is touching. Alternate locations for the pointing device and the arrangement of the keys and pointing device on the remote control will be apparent to one skilled in the art.

In one embodiment, as shown in Figure 9C, a microphone 1244, an earphone 1242, and an RF transceiver are included in remote control devices 124, providing a cordless-telephone functionality, with PC 118 being the base unit and remote control 124 being the remote unit. In another such embodiment, as shown in Figure 10, a microphone 1244, a speaker 1242, and an RF transceiver are included in remote control device 126, providing a cordless-telephone functionality, with PC 118 being the base unit and remote control 126 being the remote unit. Phone calls can be received or initiated by activating a "phone" function by pressing one or more of the control buttons on the phone, such as simultaneously pressing buttons 922 and 928, which, in one embodiment, toggles function between TV and phone, thereby automatically muting the audio of the TV when phone function is desired.

A power switch is provided at 914 to provide power-on/off functions for the monitor 122 and resume/rest for personal computer 118. Channel control buttons 916 provide the familiar television/VCR up and down channel control functions. Volume controls 918 are also provided, as is the standard number

keypad in television remote controls indicated generally at 920. Alternatively, an alphanumeric keypad, such as a standard telephone keypad, or a combination of numeric and alphanumeric keys, is provided. Further provided are mute button 922, channel recall 924, FAV (favorite channel or menu) button 926 and TV button 928, which serves to cycle the display through full screen display of a television program, to putting it in a window, to hiding it completely. An additional function set control button 930 is used to select functions provided by an operating system beyond those normally provided today. Much as the "Ctrl" and "Alt" keys are used to select different functions, the function set button 930 is similarly used on the hand held remote 124 to select the functions defined by the operating system. FAV button 926 may be unique to each family member, and comprise a listing of the users favorite television programs, games, computer application programs, home pages on Internet, or other interfaces into the electronic world.

Hand held remote 124 also contains RF generating circuitry 932 coupled to all the keys, the trigger and the pointing device for generating RF signals corresponding to the keys pressed, the status of the trigger, and the movements of the pointing device for reception by RF circuitry 324. The power of the RF signal is adjustable via a thumbwheel indicated at 934, which is coupled to further power adjusting circuitry shown in Figure 12. Power is provided by a standard 9 volt cell 936, or multiple double "A" batteries, accessible via a removable panel 940.

Remote keyboard 126, shown in further detail in Figure 10, is very similar to a MF II keyboard, except that the numeric key pad has been replaced with television/VCR like remote control buttons, and a touchpad indicated at 1010. In addition, it contains a pair of function set keys 1012 and 1014 for invoking the same functions as button 930 on handheld remote 124. The television/VCR buttons include a power button 1016, volume controls 1018, channel controls 1020, TV/VCR button 1022, mute button 1024, a favorite channel/function button 1026 and a channel recall button 1028. In addition, selection keys 1030 and 1032 are provided to select function indicated by the

cursor as controlled by touchpad 1010. Touchpad 1010 is integrated into the remote keyboard, and permits easy manipulation of the cursor by simply moving an object, such as a pen, stick or finger/finger nail across the pad in the desired direction. It can be useful for performing signatures to validate transactions, or
5 restrict access to files. By integrating touchpad 1010 directly in the remote keyboard 126, there are no external connections, or sliding drawers to contend with, which could easily become clogged with grease, butter, sugar or any of the other messy things people eat while being entertained in a family entertainment center. The portion of the keyboard containing the television/VCR remote
10 controls is preferably sealed, and impervious to being affected by such foods and drinks as are commonly found in a family room. Since the keyboard is more likely to be heavily used, a higher number of double "A" batteries are used. Four to eight provide a suitable length of operation. They may be rechargeable, and an external power jack 1042 is provided to allow the keyboard to be plugged into
15 standard electrical utility power supplies.

As with the handheld remote 124, the keyboard remote 126 comprises RF generating circuitry 1040 to provide RF signals for reception by RF circuitry 324 in personal computer 118. RF circuitry 1040 also adds on a keyboard identifier with the signals it transmits, which identifies each keystroke as
20 originating from the keyboard. In one embodiment, it is a set of bits that is unique to the remote device. This helps prevent inadvertent interference from other owners of similar home entertainment systems from inadvertently controlling the users system. In another embodiment, the frequency is shifted slightly from that emitted by the handheld remote, and RF circuitry 324 detects
25 the bits, or the frequency shift and identifies the keystrokes as originating from either the handheld remote, or the remote keyboard which is associated with the system. In yet a further preferred embodiment, multiple remotes are provided, each with its own identifying frequency or code, including joysticks for controlling games. In this manner, each individual in the room can be
30 controlling their application or program in a window, or be playing different parts in a game. Since all remotes would be sending the same signals to

represent the same functions, the drivers for such remotes running on processor 310 need not differ. They need only be designed to handle multiple different sources of the keystrokes, button strokes, mouse, stick or touchpad signals.

A high level flowchart showing how commands issued from different remote control devices are interpreted by processor 310 to control different applications is shown in Figure 11a. When an application is started in a Windows 3.11 or 95 environment, it is initialized as shown at 1110 to be associated with a particular remote. The keys or buttons from such remote are identified in groups of either "keyboard" or "TV" or "game" type keys. Game type keys would be those associated with the stick, trackball or mouse type of pointing devices. Thus, an application could be associated with game keys from the handheld remote for one player of a game, and game keys from the keyboard remote for a second player. Further remotes, or different groups from a remote could be used for further players. When RF circuitry 324 receives signals from a remote, it identifies the command, such as what key was pressed, and which remote device it came from to processor 310 at step 1112. Processor 310 then identifies the application in a window to which it should be applied. If it is a presentation type of command, such as enlarging a window or opening a window as determined at 1116, the command is routed to the window manager for execution at 1118. If not, it is executed on the application that the group it is associated with was initialized to at step 1110. In further preferred embodiments, individual keys are associated with applications, however, at least one group or key is always associated with the underlying operating system to prevent a user from being locked out of other applications. One further use of the above system is to assign TV/VCR controls to television programming associated with a window. In this manner, no cursor need be present in the window, blocking the television programming in order to perform channel selection. In addition, if someone else is watching a program in a different window, their channel selection controls will only affect their window.

A block diagram in Figure 11b represents tables formed by a program manager to associate remote control devices and the input devices on the remote

control devices to programs. Programs, as used herein refer to computer application programs and television programs, both of which are controllable by remote control devices. A first program 1122 is associated with a first remote controller, R1, whose input devices D1 and D2 control the first program. D1 and D2 correspond to the alphanumeric keys, such as a computer keyboard keyset, or subset thereof, or a cursor control device, or even the television control pad previously discussed. Second, third and fourth programs 1124, 1126, and 1128 are also associated with remote control devices, and in some instances multiple remote control devices. Fourth program 1128 is controlled by input device sets D1 and D2 of remote R1, and D1 and D2 of the second remote R2. The low level granularity of associating sets of keys to applications provides great flexibility for a multi-user home entertainment system.

In a further embodiment, FM earphone headsets are provided to enable each person to hear only the sound that is associated with their own window of programming. The sound associated with each program is either assigned to one of several standard FM frequencies and broadcast in low power, much like that in a drive-in movie theater, and each headset is tunable to the frequencies broadcast. In another embodiment, each headset is tuned to a different single frequency, and the user selects the windows whose sound will be broadcast on which frequencies. The top most window in such a set of windows will have its audio so broadcast.

Further detail of RF circuitry in the remote control devices is shown in Figure 12. An input device, comprising the keyboard or hand held remote is indicated at 1210. When a key, touchpad command, trackball etc command is activated, it is provided to a decoder 1212, which decodes the command into a signal representative of the command to be transmitted. It also adds a header and check bits to the signal to be transmitted, indicating a unique identification of the remote. The identification in one embodiment is a digital signal which is unique for each remote control for one system and stored on an EE-PROM, while in a further embodiment, the code is an eight bit, or a 16 bit code which results in over 64,000 different combinations, making it unlikely that neighbors within

range will have remotes with codes that will control a user's system. The unique identifier may also be represented by selecting a different frequency for each remote control device. The system uses this unique identification as described above to determine which program should be affected by the particular command
5 issued from the particular remote that issued it.

The Decoder 1212 provides a decoded signal to an FM signal source and modulator 1214, which in one embodiment generates a desired RF signal in the 900 megahertz region of the electromagnetic spectrum. This signal is provided to a power amplifier 1216, which amplifies the RF signal and provides it to an
10 antenna 1218 for transmission to the system. The power amplifier 1216 consumes most of the power in the remote control device. A potentiometer 1222 is provided to reduce the gain of the amplifier so that it is not always amplifying the signals at the highest power level. Since users will vary the distance they are from the system, there is no need to always transmit at the maximum power
15 level. If a user is close to the system, the user may adjust the power level downward by turning the thumb wheel on the remote in the appropriate direction until the system no longer receives the transmissions. In one embodiment, the receiver in the system detects the signal strength received, and provides visual feedback on the display to assist the user in setting the power level to a level
20 where no errors in transmission due to low power signals are likely to result. Such signal power level detectors are well known in the art, and one example is shown in US Patent No. 5,193,210. In a further embodiment, the RF receiver 324 also comprises an RF transmitter, and provides an RF signal representative of the power level back to the remote, which is received by a receiver antenna
25 1224. Antenna 1224 is coupled to a receiver/demodulator/decoder 1226 which decodes the signal and provides a digital signal representative of transmitted signal strength back to a power control circuit 1228. Power control circuit 1228 is coupled to the potentiometer 1222 for adjustment of the gain of power amplifier 1216 based on the signal strength feedback from the system. Power
30 control circuitry 1228 is also coupled to the input device, to sense when commands are entered. It is also coupled to the other components to control

when they are supplied power. During touchpad and trackball operation, power is supplied continuously to all the electronics. However, after a predetermined period of time, approximately 1 second, with no further commands being sensed, the power control circuitry 1228 cuts off power to most of the other circuitry, and only turns it back on within milliseconds when activity on the input device 1210 is detected. When other circuitry is powered off, the power control circuit remains active, along with the receiver 1226. The power control circuit 1228 buffers commands until the other circuitry is ready to process the commands. Since it turns back on quickly, there is no perceptible delay by the user.

10 In a further embodiment, each input device command transmitted is acknowledged by the system with an echo of the command. When no acknowledgment is received, the power control circuitry 1228 instructs the decoder to send the signal again, while increasing the power level until the system properly acknowledges the command. All other commands are buffered
15 in the power control circuitry until successful transmission of the command, whereupon they are transmitted at the new adjusted power level. In one embodiment, the times for rebroadcast are randomly chosen, and prevented if the receiver 1226 detects transmissions from another remote control device or the system to prevent interference. This is not done if each remote has its own
20 transmission frequency, which is set, in one embodiment, by a DIP switch 1240.

In yet another embodiment, the remote control devices are used as a "speakerphone," a hands-free intercom-like connection to the telephone system. In conjunction with the modem telephone functions, the RF circuitry 324 transmits and receives in a manner equivalent to the base unit of a cordless
25 phone. A speaker 1242 on the remote control device is coupled to the receiver 1226, which receives RF voice from the RF circuitry 324, and provides the received sound. A microphone 1244 is coupled to the decoder 1212 for transmitting sound created by the user. Receiver 1226 and decoder 1212 operate in conjunction as the handset of a standard cordless phone. In a further
30 embodiment, the earphone headsets are used in place of the speakers for privacy. In one embodiment, a headset jack is provided in the remote control device as

part of the block indicating speaker 1242 and standard headsets may be used. Still further uses for the RF transceiver circuitry in the remote control device will be apparent to those skilled in the art. It should be noted that other frequencies of electromagnetic waves may be used without departing from the spirit and
5 scope of the invention.

When the user receives a telephone call, a message appears on the display with the identity of the calling source if caller ID is provided by the telephone service selected. This allows easy interface into available databases to "pull" up further information about the caller stored on the system. A key 931 on the
10 remote is used to answer the call. The keypad is used to enter numbers, with the modem providing standard DTMF (dual-tone, multiple-frequency) tones.

The remotes 124 and 126 also contain jacks 942 and 1044 for game controller input. A standard personal computer analog game port is provided, or in conjunction with the RF transceiver capability of the remote control devices, a
15 bi-directional digital port is provided from jacks 942 and 1044.

One example of the advantages of having a full function computer operating in conjunction with broadband video is that it opens up the power of a personal computer to control the video streams and advanced user functions. The interface to the broadband video is much more user friendly. In Figure 13,
20 one example is shown, with a standard television like schedule indicated generally at 1310. It comprises a timeline across the top, starting at 8 PM and progressing to midnight. Four channels, A, B, C and D are shown, but many more may be available. Other programs, such as games and word processors which may be selected in standard double mouse click fashion are also shown.
25 Both the time frames and the number of channels shown may be modified by the user enlarging the window using standard Windows based navigation techniques. Multiple cells, or programs are shown on each channel, and are represented as a suffix of the channel letter for discussion herein. In actuality, program titles and descriptions appear be inserted in each cell. By clicking on a cell with the right
30 mouse button, further details appear in an expanded version of the cell.

Several icons are tied to functions controlled by the system. A record icon 1320 is tied to either a separate video cassette recorder, the tape drive, or the disk drive to record selected channels. A program cell may be indicated for recording by dragging the cell with a mouse control and dropping it onto the record icon. Similarly, a reminder may be set by dropping a program cell onto a remind icon 1322. If a pay per view program is desired, one simply drags the program cell, which is perhaps outlined in green, over on top of a buy icon 1324. The buy icon is also used when viewing a home shopping channel, or a catalog in a similar manner. To view a primary program, a user either double clicks on a cell, or drags a cell to a view icon 1326 and drops it there. To place a program into a picture in picture format, a user drags a cell onto a PIP icon 1328. The picture in picture window may then be resized like any other window, or moved to another area of the display. All the icons may also be arranged in an L-shape surrounding a primary channel being viewed so that the icons do not interfere with the video images being displayed from the primary channel.

In one embodiment, each remote control device controls a different cursor, shown as R1 and R2 on the screen in Figure 13. When the cursor is used to select a program, it becomes the primary controller for that program. The keys on the remote are automatically mapped into the program selected. The keyboard however, retains control of the task list, and is capable of selecting a program and becoming the primary control device for that program to the exclusion of the hand held remote control device.

In Figure 13, icons E1 and E2 represent remote earphones. The personal computer sound card 320 also contains a multi frequency FM transmitter 646 with antenna 648, and has the capability to generate separate sound tracks for each window being displayed on the monitor. It assigns each to one or more sets of earphones and transmits a local FM signal or broadcast IR or RF which is received and played by the earphones set to the right channel. The earphones have tuning circuitry that allows them to be set to a desired channel, or they may be fixed to different frequencies. The user drags the appropriate icon over to the program having the desired sound track, or to the remote that the user is

controlling and drops it. If dropped on a program, the sound card transmits the sound for that application on the frequency associated with the earphones which are tuned to that frequency. If it is dropped on a remote control device, the top window associated with that remote has the sound associated with it transmitted.

5 A first screen display provided on monitor 122 to users is shown in block diagram form in Figure 14a. The display comprises a set of icons which are tied to underlying functions in a Microsoft Windows95 or down level version operating environment. This front end is specifically designed to be a replacement shell for the normal Windows operating environment to make it
10 user friendly to a family. It acts as an application manager, allowing the user to launch other applications and utilities from within it. The front end is organized into the following areas, each of which leads to further menus: Entertainment, Information Services, Productivity, and Logon/Help/Configuration controls. The front end utilizes Win32c application program interfaces, and operates both
15 as a shell and as a stand-alone application. It supports drag and drop and is Win95 logo compliant.

Further icons on the first screen comprise a logon icon for bringing up a dialog box asking for the user name and password and a help icon for bringing up a context sensitive help engine with a data file which is related to the screen
20 where the help icon was selected. The dialog box for the logon contains an option for a default, or family logon which may not require a password.

The front end splits the integrated video processing, audio processing and data processing functionality of the entertainment system into different areas of similar functionality as show in the block diagram of Figure 14b, comprising an
25 entertainment icon 1410, an information services icon 1412 and a personal productivity icon 1414. Each of these icons, when activated by clicking, or from a task list invoke further menus. An entertainment menu in a window on the monitor is shown in Figure 14c, comprising selections such as Microsoft Home Theater, CD audio, Digital Video, IR Blaster and Games, all of which may be
30 launched from this window. The Games icon provides a user configurable games menu, which has the capability of being user aware, provided the user

identified himself or herself at login. The person logged on is also noted at the bottom of the window. Each user is then able to have their favorite games listed when they are logged in. A home icon or control button is active, and takes the user back to the main menu. Help controls are also active, and take the user to context sensitive system and help information.

The Information Services icon 1412 leads to a further Information Services Menu as shown in Figure 14d. Many commercially available information services are launchable, as well as telephony related functions tied to the modem, such as voice messages, fax viewing and mail readers.

The Personal Productivity icon 1414 leads to a Personal Productivity menu in Figure 14e, where personal productivity software is launchable. While shown as a text based list, the applications may also be represented by icons.

A configuration menu is shown in Figure 14f and is found through the first screen display. Cancel is the active button in this menu due to the potential to adversely affect the look and operation of the entertainment system. A user can change the front end to essentially a computer program based interface, change the clock of the system, browse the secondary storage for other applications which can be dragged and dropped onto different menus, and remove applications from different menus.

One embodiment, implemented on a circuit card or cards for providing video conferencing via a public switched telephone network is shown generally at 1510 in Figure 15. Broken line block 1511 implements an industry standard, such as the proposed ITU-T (International Telecommunications Union-Telecommunications) standard, and each element described hereinafter within block 1511 implements the standards that are identified in the element block. Input/output devices comprising a microphone 1512 and speaker 1514 are coupled to a signal converter 1516. Converter 1516 converts signals from the microphone to digital signals, and digital signals to analog speakers for driving the speaker 1514. Converter 1516 is coupled to an echo canceling device 1518 for reducing feedback between the speaker and microphone. An audio coder/decoder 1520 is coupled to both the cancelling device 1518 and converter

1516, and to a delay circuit 1522, which in turn is coupled to a multiplexor/demultiplexor 1524 for processing the audio signals. Multiplexor 1524 is in turn coupled to a modem 1526, which has capability for both sending and receiving data on a public switched telephone network ("PSTN") indicated at
5 1528 in either analog (such as a modem connected to an analog "POTS" or plain old telephone system) or digital (such as a digital ISDN connection) form.

A video camera 1532 (which can be a stand-alone video camera, a commercially available camcorder, or other imaging device) is coupled to suitable video inputs on back panel 710, and is used to provide a video feed to a
10 color space convertor/graphics display module 1535, which provides a further video signal to a video coder/decoder 1536, which is coupled to the multiplexor 1524. Video signals received from the camera are compressed by the codec (coder/decoder) 1536, and then transmitted over the telephone network by modem 1526. Video signals received from the network by modem 1526 are
15 demultiplexed, decompressed and turned into signals (in one embodiment, into VGA signals) for display on a monitor. In addition to providing the ability to perform video conferencing with other compatible systems over a telephone network, several data-exchange protocols are supported at a data converter 1540, which is coupled between the multiplexor 1524 and a data storage device 1542
20 containing data generated by a user application. A system control icon 1544 represents the ability of the operating system of a computer, such as the computer comprising the home entertainment system, to control the elements of the video conferencing circuitry. System control 1544 is coupled to a system control block 1546, which implements standard H.246 and in turn is coupled to
25 both the multiplexor 1524 and modem 1526 to provide operator control thereof.

A further embodiment of a video conferencing aspect of the home entertainment system is shown in Figure 16 generally at 1610. Common components of the home entertainment system are numbered the same as in previous figures. In this implementation, a plain old telephone system ("POTS")
30 connection 1612 (which is alternatively a digital connection such as ISDN into the PSTN) can also be used for the video, sound and data signal transmission.

Other users to be connected by video conference are represented at 1614. A camcorder 1616 (which can be a stand-alone video camera, a commercially available camcorder, or other imaging device) is used to provide the audio/video feed via the back panel inputs 710, where the video and audio are then provided to the sound 320 and converter 318 cards for digitization. The digitized signals are then sent through the system bus to the modem 322 for transmission. Received signals via the modem are sent to the CPU, sound card, and video card for decompression and/or playing on monitor 122 and/or a stereo/speaker combination 1620. Elements indicated with broken lines, are advanced features which are easily implementable. They include a voice capability coupled to the sound card 320 and modem 322 for providing a separate voice channel when video conferencing is not desired. A set of amplified speakers are indicated at 1624 which are driven directly by the sound card 320 with no need for independent amplification. A digital camera with microphone indicated at 1628 is coupled directly to a digital signal processor (DSP) with mixing and decoding functions indicated at 1630. The DSP 1630 is coupled directly to the system bus 312. Finally, a video cassette recorder 1632 is coupled to the converter card 318 for recording.

While the system has been described in terms of a personal computer, it is easily modified to encompass a settop box version, where all the circuitry is integrated into one or two cards in a box designed to sit on top of a television having VGA input. In another version, all the circuitry is included inside of the television chassis.

It is to be understood that the above description is intended to be illustrative, and not restrictive. Many other embodiments will be apparent to those of skill in the art upon reviewing the above description. The scope of the invention should, therefore, be determined with reference to the appended claims, along with the full scope of equivalents to which such claims are entitled.

What is claimed is:

1. A hand held remote control device for an entertainment system comprising:
 - 5 a trigger-like selection button located on a bottom portion of the remote control device such that the button is convenient to the index finger of a hand for selecting functions associated with a cursor displayed on a screen of the entertainment system when the device is held in the hand; a pointing device for controlling the cursor displayed on the
 - 10 entertainment system; and
 - electromagnetic frequency generating circuitry coupled to a plurality of keys for transmitting signals representative of the button and pointing device.
- 15 2. The hand held remote control device of claim 1 further comprising a trigger guard located on the bottom portion of the remote control device and partially shrouding the trigger-like selection button to prevent accidental activation of the button.
- 20 3. The hand held remote control device of claim 1 wherein the pointing device is a trackball integrated into the hand held device.
4. The hand held remote control device of claim 1 wherein the pointing device is a miniature joystick for operation by a finger tip.
- 25 5. The hand held remote control device of claim 1 wherein the pointing device is a touchpad.
6. The remote control device of claim 1 wherein the electromagnetic
- 30 frequency generating circuitry generates signals to be transmitted in the radio

frequency range so that the receiver does not need to be located in direct line of sight with the transmitter.

7. The remote control device of claim 1 wherein the electromagnetic
5 frequency generating circuitry generates signals to be transmitted in the infrared range.

8. A hand held remote control device for an entertainment system comprising:

10 a top portion having a plurality of keys disposed thereon for selecting alphanumeric symbols and cursor control functions;
a trigger-like selection button located on a bottom portion of the remote control device such that the button is convenient to the index finger of a hand for selecting functions associated with a cursor displayed on a
15 screen of the entertainment system when the device is held in the hand;
a pointing device for controlling the cursor displayed on the entertainment system; and
electromagnetic frequency generating circuitry coupled to the plurality of
keys for transmitting signals representative of the selected keys, the
20 button and the pointing device.

9. The hand held remote control device of claim 8 further comprising a trigger guard located on the bottom portion of the remote control device and partially shrouding the trigger-like selection button to prevent accidental
25 activation of the button.

10. The hand held remote control device of claim 8 wherein the pointing device is a trackball integrated into the hand held device.

30 11. The hand held remote control device of claim 8 wherein the pointing device is a miniature joystick for operation by a finger tip.

12. The hand held remote control device of claim 8 wherein the pointing device is a touchpad.
13. The remote control device of claim 8 wherein the electromagnetic
5 frequency generating circuitry generates signals to be transmitted in the radio frequency range so that the receiver does not need to be located in direct line of sight with the transmitter.
14. The remote control device of claim 8 wherein the electromagnetic
10 frequency generating circuitry generates signals to be transmitted in the infrared range.
15. A hand held remote control device for an entertainment system controlled by a personal computer having software that specifies operations of the
15 entertainment system to be executed when certain electromagnetic signals are received by the computer, the remote control device comprising:
a top portion having a plurality of keys disposed thereon for selecting alphanumeric symbols and cursor control functions;
a trigger-like selection button located on a bottom portion of the remote
20 control device such that the button is convenient to the index finger of a hand for selecting functions associated with a cursor displayed on a screen of the entertainment system when the device is held in the hand;
a pointing device for controlling the cursor displayed on the entertainment system; and
25 electromagnetic frequency generating circuitry coupled to the plurality of keys for transmitting signals representative of the selected keys, the button and the pointing device, wherein one of the plurality of keys transmits a remap signal that activates the software.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9A




FIG. 9B




FIG. 9C




FIG. 10




FIG. 11A




FIG. 11B





FIG. 12

FIG. 13






FIG. 14A




FIG. 14B

ENTERTAINMENT MENU			
MHT		GAMES	
CD AUDIO			
DIGITAL VIDEO			
IR BLASTER			
HOME	12:00PM	LOGGED IN AS: <u>FAMILY</u>	HELP

FIG. 14C

INFORMATION SERVICES MENU			
COMPUSERVE		VOICE MESSAGES	
PRODIGY		FAX VIEWER	
AMERICA ONLINE		UNIVERSAL MAIL READER	
INTERNET			
HOME	12:00PM	LOGGED IN AS: <u>FAMILY</u>	HELP

FIG. 14D

PERSONAL PRODUCTIVITY MENU			
WORKS		ENCARTA	
QUICKEN		DICTIONARY	
TURBOTAX			
HOME	12:00PM	LOGGED IN AS: <u>FAMILY</u>	HELP

FIG. 14E

CONFIGURATION MENU				
CLOCK-TIME: <u>12:00PM</u> , FONT: <u>ARIAL</u>				
FRONT END OR WIN95? <u>FRONT END</u>				
GAMES	IS	PP	BROWSER	
<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>	<input type="text"/>
HOME	12:00PM	LOGGED IN AS: <u>FAMILY</u>	HELP	

FIG. 14F




FIG. 15




FIG. 16

INTERNATIONAL SEARCH REPORT

Int. Application No.
PCT/US 97/04003

A. CLASSIFICATION OF SUBJECT MATTER

IPC 6 G06K11/18

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 6 G06K

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5 339 095 A (REDFORD PETER M) 16 August 1994 see column 4, line 1 - line 20 see column 9, line 40 - line 51	1,6-8, 13-15
Y	---	3-5, 10-12
Y	DE 44 00 668 A (THOMSON BRANDT GMBH) 20 July 1995 see column 1, line 57 - column 2, line 45; figures 1-3	3,10
Y	IBM TECHNICAL DISCLOSURE BULLETIN, vol. 31, no. 11, April 1989, page 288/289 XP000052233 "TELESCOPIC JOYSTICK" see the whole document ---	4,11
	-/--	

☒ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

* Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
- *&* document member of the same patent family

Date of the actual completion of the international search

7 July 1997

Date of mailing of the international search report

18.07.97

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+ 31-70) 340-2040, Tx. 31 651 epo nl,
Fax (+ 31-70) 340-3016

Authorized officer

Bailas, A

INTERNATIONAL SEARCH REPORT

Int onal Application No

PCT/US 97/04003

C.(Continuation) DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
Y	DE 90 04 566 U (CHICONY ELECTRONICS GMBH) 16 August 1990 see page 2, line 1 - line 20 ---	5,12
A	PATENT ABSTRACTS OF JAPAN vol. 018, no. 029 (E-1492), 17 January 1994 & JP 05 260559 A (MATSUSHITA ELECTRIC IND CO LTD), 8 October 1993, see abstract -----	5,12

INTERNATIONAL SEARCH REPORT

Information on patent family members

Int onal Application No

PCT/US 97/04003

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
US 5339095 A	16-08-94	US 5459489 A	17-10-95
DE 4400668 A	20-07-95	NONE	
DE 9004566 U	16-08-90	NONE	